

HTI-A-S16

16 high-power power sequencer



Features

- Built-in 16-way universal socket relay controlled socket;
- With sequential opening and reverse closing, the PASS key can open all channels at the same time;
- With precise voltage display, support panel independent control of each channel, panel channel independent closing;
- The switch interval time/timing time of each channel is 1 second;
- Support stacking cascade function;
- With six stable protections of voltage stabilization, short circuit, overheating, overcurrent, overvoltage and over discharge;
- The output power socket is made of flame-retardant ABS material, can withstand a maximum current of 13A, phosphor copper material, standard universal socket;
- Single-channel power is 2000W, total power is 6000W;
- Wide-range voltage power AC100-240V 50-60Hz;

Conference Audio System

Technical parameters	
Display	2-inch LCD screen
Number of relays	16
Scene saving	10
Single channel power	2000W
Supply voltage	AC100V~240V; 50/60Hz
Control interface	RS-232*1
Dimension	485x277x90mm
Net weight	5.5kg
Gross weight	6kg

Design and specifications are subject to change without notice.

Pictures in the document are for reference only, and the actual product shall prevail.